

forming a lightly-doped source/drain region with only a first dopant, the lightly-doped source/drain region located between first and second isolation structures; and creating a gate over the lightly-doped source/drain region.

2. (Original) The method as recited in Claim 1 wherein forming includes forming a lightly-doped source/drain region with a first N-type dopant.

3. (Original) The method as recited in Claim 2 wherein the first N-type dopant has an implant dose ranging from about $1E12$ atoms/cm² to about $1E13$ atoms/cm².

4. (Original) The method as recited in Claim 3 wherein the first N-type dopant has an implant dose of about $5E12$ atoms/cm².

5. (Original) The method as recited in Claim 1 further including diffusing a second dopant at least partially across the lightly-doped source/drain region and under the gate to form a first portion of a channel.

6. (Previously Presented) The method as recited in Claim 5 wherein diffusing the second dopant includes diffusing a P-type dopant having an implant dose ranging from about $1E13$ atoms/cm² to about $1E14$ atoms/cm².

7. (Previously Presented) The method as recited in Claim 5 wherein diffusing the second dopant includes diffusing a P-type dopant having an implant dose about 100 times higher than an implant dose of the first dopant.

8. (Original) The method as recited in Claim 5 further including placing a heavy concentration of the first dopant in a region adjacent a source side of the gate, and in the lightly-doped source/drain region adjacent a drain side of the gate.

9. (Original) The method as recited in Claim 8 wherein placing includes placing the heavy concentration of the first dopant in the lightly-doped source/drain region a distance ranging from about 2000 nm to about 3000 nm from the drain side of the gate.

10. (Original) The method as recited in Claim 8 wherein placing includes placing an implant dose of the first dopant ranging from about $1E15$ atoms/cm² to about $1E16$ atoms/cm².

11. (Previously Presented) A method of manufacturing an integrated circuit, comprising:

fabricating laterally diffused metal oxide semiconductor (LDMOS) transistors, including:

forming a lightly-doped source/drain region with only a first dopant, the lightly-doped source/drain region located between first and second isolation structures; and

creating a gate over the lightly-doped source/drain region;

depositing interlevel dielectric layers over the LDMOS transistors; and

creating interconnect structures in the interlevel dielectric layers and interconnecting the LDMOS transistors to form an operative-integrated circuit.

12. (Original) The method as recited in Claim 11 wherein forming includes forming a lightly-doped source/drain region with a first N-type dopant.

13. (Original) The method as recited in Claim 12 wherein the first N-type dopant has an implant dose ranging from about $1E12$ atoms/cm² to about $1E13$ atoms/cm².

14. (Original) The method as recited in Claim 13 wherein the first N-type dopant has an implant dose of about $5E12$ atoms/cm².

15. (Original) The method as recited in Claim 11 further including diffusing a second dopant at least partially across the lightly-doped source/drain region and under the gate to form a first portion of a channel.

16. (Previously Presented) The method as recited in Claim 15 wherein diffusing the second dopant includes diffusing a P-type dopant having an implant dose ranging from about $1E13$ atoms/cm² to about $1E14$ atoms/cm².